

ProCurve Networking Mini-GBIC and SFP Support Matrix

ProCurve Switch Series	Software Versions	Genuine ProCurve rev A Gig-SX, LX, LH (J4858A, J4859A, J4860A)		Gig-SX, LX, LH (J4858B, J4859B, J4860B)		Genuine ProCurve rev B Gig-T ¹ (J8177B)		100-FX (J9054B)		Genuine 3rd Party "rev A" from ProCurve Vendors ²		Non-Genuine ProCurve "rev A" ³	
		Supported? ⁴	Functions? ⁵	Supported?	Functions?	Supported?	Functions?	Supported?	Functions?	Supported?	Might Function? ⁶	Supported?	Might Function?
1400-24G (J9078A)	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
1700-24 (J9080A)	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
1800-24G (J9028A)	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
2510-24 (J9019A)	Q.10.01 - Q.10.03	no	no	yes	yes	no	no	no	no	no	no	no	no
	Q.10.04 and later	no	no	yes	yes	no	no	yes	yes	no	no	no	no
2600 'A' (J4899A, J4900A)	H.07.02 - H.08.81	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	H.08.82 - H.08.97	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	H.08.98 and later	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
2600-PWR (J8164A, J8165A)	H.07.41 - H.08.81	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	H.08.82 - H.08.97	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	H.08.98 and later	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
2600 'B' (J4899B, J4900B)	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
2810	N.10.02 - N.10.06	no	no	yes	yes	no	no	no	no	no	no	no	no
	N.10.07 and later	no	no	yes	yes	no	no	yes	yes	no	no	no	no
2824/2848 (serial # < SG505xxxxx)	i.07.31 - i.08.80	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	i.08.81 - i.08.97	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	i.08.98 - i.10.28	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	i.10.30 and later	yes	yes	yes	yes	no	no	yes	yes	no	yes	no	yes
2824/2848 (serial # >= SG505xxxxx)	i.07.31 - i.08.50	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	i.08.51 - i.08.102	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
	i.08.103 - i.10.28	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
	i.10.30 and later	yes	yes	yes	yes	no	no	yes	yes	no	yes	no	yes
2900	T.11.01 - T.11.13	no	no	yes	yes	no	no	no	no	no	no	no	no
	T.12.01 and later	no	no	yes	yes	no	no	yes	yes	no	no	no	no
3400cl	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	no
3500yl	K.11.11 - K.11.69	no	no	yes	yes	no	no	no	no	no	no	no	no
	K.12.01 and later	no	no	yes	yes	no	no	yes	yes	no	no	no	no
4100gl	all versions	yes	yes	yes	yes	yes	yes	no	no	no	yes	no	yes
4200vl	L.10.01 - L.10.23	no	no	yes	yes	yes	yes	no	no	no	no	no	no
	L.10.24 and later	no	no	yes	yes	yes	yes	see footnote 7	yes	no	no	no	no
5300xl	E.05.04 - E.10.04	yes	yes	yes	yes	yes	yes	no	no	no	yes	no	yes
	E.10.05 - E.10.35	yes	yes	yes	yes	yes	yes	no	no	no	yes	no	no
	E.10.36 and later	yes	yes	yes	yes	yes	yes	no	no	no	yes	no	yes

ProCurve Switch Series	Software Versions	Genuine ProCurve rev A Gig-SX, LX, LH (J4858A, J4859A, J4860A)		Gig-SX, LX, LH (J4858B, J4859B, J4860B)		Genuine ProCurve rev B Gig-T ¹ (J8177B)		100-FX (J9054B)		Genuine 3rd Party "rev A" from ProCurve Vendors ²		Non-Genuine ProCurve "rev A" ³	
		Supported? ⁴	Functions? ⁵	Supported?	Functions?	Supported?	Functions?	Supported?	Functions?	Supported?	Might Function? ⁶	Supported?	Might Function?
5400zl	K.11.11 - K.11.69	no	no	yes	yes	yes	yes	no	no	no	no	no	no
	K.12.01 and later	no	no	yes	yes	yes	yes	yes	yes	no	no	no	no
6108	all versions	yes	yes	yes	yes	no	no	no	no	no	yes	no	yes
6200yl	K.11.11 - K.11.69	no	no	yes	yes	yes	yes	no	no	no	no	no	no
	K.12.01 and later	no	no	yes	yes	yes	yes	yes	yes	no	no	no	no
8100fl	all versions	no	no	yes	yes	yes	yes	no	no	no	no	no	no
9300m	all versions	yes	yes	yes	yes	see footnote 8	yes	no	no	no	yes	no	yes
9408sl	all versions	yes	yes	yes	yes	yes	yes	no	no	no	yes	no	yes



ProCurve Networking Mini-GBIC and SFP Support Information

- ProCurve products and accessories offer a lifetime warranty, unsurpassed in the marketplace.
- ProCurve Networking stands behind our products because we build them to precise specifications and thoroughly test them.
- ProCurve mini-GBICs and SFPs are specified and tested as rigorously as the devices in which they are used.
- Non-ProCurve mini-GBICs and SFPs are of unknown quality and therefore cannot be supported with our lifetime warranty.

Footnotes

¹ The J8177B Gig-T (1000Base-T) mini-GBIC is not supported in dual-personality ports. Also, see the minimum software requirements in the document "Support for the J8177B 1000Base-T Mini-GBIC", available on the mini-GBIC FAQ Web page at www.hp.com/rnd/support/faqs/mini-GBICs.htm.

² 3rd party products from non-ProCurve vendors are not supported and will not function.

³ Non-genuine ProCurve "rev B" mini-GBICs are not supported and will not function.

⁴ Supported: Qualified for operation in ProCurve switches and for warranty support from ProCurve Networking.

⁵ Functions: This ProCurve mini-GBIC works properly in the listed ProCurve switch series.

⁶ Might function: The ProCurve switch attempts to enable this non-ProCurve mini-GBIC.

⁷ For the 4200vl series, the J9054B 100-FX SFP-LC transceiver is supported only in the J9033A module, with software version L.10.24 and later.

⁸ For the 9300m series, the J8177B Gig-T (1000Base-T) mini-GBIC is supported only on EP modules, with software version 07.8.00a and later.