

Firmware Release Note

Model : SL-C430, C430W	Date :	March 15, 2018
-------------------------------	---------------	-----------------------

Version	Category	Change Description
V3.00.01.09 (4-Jan, 2016)	Fix Defect	Fix print quality issues(pollution and text quality)
V3.00.01.13 (31-Oct, 2016)	Fix Defect	Last page doesn't print when user prints odd page document with manual duplex option
V3.00.01.14 (11-July, 2017)	Fix Defect	Fix toner cartridge recognition error
V3.00.01.15 (15-Mar, 2018)	Fix Defect	Block device warm up when connecting through Wi-Fi Direct. (Wireless model only)
		Fix print quality(background) issue


※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
- If you are using USB connection, disconnect all other USB printers from the PC.
- The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Drag 'SWUPGRADE_ON.prn' and Drop down it on usblist2.exe.
3. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.

And then, firmware update will be started automatically.



4. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.
Login as Admin in SyncThruWeb Service.
NOTE: Login using the Administrator ID and Password established during initial machine setup.
2. Click [Maintenance] on the top menu.
And then click [Firmware Upgrade] or Application Management > Application
3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.