

Firmware Release Note

Model : SL-C1810W	Date :	December 7, 2016
--------------------------	---------------	-------------------------

Version	Category	Change Description
V4.00.02.11 (30-Apr, 2014)	Fix Defect	- Photo Print Quality & Copy Text Improvement. - New Blue Angel Certification
V4.00.02.15 (7-Aug, 2014)	Add Func.	Add Samsung Cloud Print Function
V4.00.02.22 (17-Nov, 2014)	Fix Defect	Remove unused Network Port such as TCP 22 port.
	Add Func.	Google Cloud Print 2.0 feature
	Fix Defect	Not display Hebrew download font.
V4.00.02.28 (7-May, 2015)	Add Func.	Apply PostScript
V4.00.02.31 (2015-10-5)	Add Func.	Apply the QR Code on Configuration Report
		Apply new font in PCL5, PCL6
		Apply to Toner Status and Easy setup of Samsung Cloud Print
	Fix Defect	SSL connection failed
		Auto Color Registration value storing when factory memory clear is executed
V4.00.02.32 (7-Dec, 2016)	Add Func.	Added "Network Connection Status" to Network Configuration Report
	Fix Defect	New toner count' value is incrementing with every door open-close.


※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
 - If you are using USB connection, disconnect all other USB printers from the PC.
 - The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
- Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Menu > Setup > Admin Setup > Firmware Upgrade > ON
3. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.

And then, firmware update will be started automatically.



4. The firmware update will start.

Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.
Login as Admin in SyncThruWeb Service.
NOTE: Login using the Administrator ID and Password established during initial machine setup.
2. Click [Maintenance] on the top menu.
And then click [Firmware Upgrade] or Application Management > Application
3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.