Firmware Release Note

SAMSUNG BUSINESS

Model : SL-C2620DW	Date :	July 21, 2016


Version	Category	Change Description
V4.00.01.17 (17-Nov, 2014)	Fix Defect	Improve the NFC connection
		Open source notice update
		Touch is not working in Calibration window
		C5-1710 issue related control of ITB T1 Engage
		Not display Hebrew download font.
		Once Auto Tray is configured, Print Tray is selected in wrong.
V4.00.01.28 (12-Jan, 2015)	Add Func.	Support new solutions(BCPS, SecuThru Lite)
V4.00.01.35 (12-Oct, 2015)	Fix Defect	When user install an invalid application via SyncThru Web Service(SWS), User cannot access to SWS and network status of device is not available.
		With recent Google Cloud Print(GCP) server security patches applied, GCP does not work properly.
		AirPrint performance is improved.
		Chinese string displayed at some places are wrong.
		[BCPS1.2/XOA Web] Support color print authorization
		[SWAS Job Accounting]Device didn't send a reponse to SWAS
		UI Touch response time enhencement
		ACR value storing when factory memory clear is executed
		Fixed SSL Connection bug
	Add Func.	Support Proxy Authentication
		Apply to PrinterOn Branded Agent
		Added "Network Connection Status" to Network Configuration Report
		QR code printed on Configuration Report. QR code has information regarding Model Name, Serial number and MAC address of the device.
		Apply new font data in PCL5, PCL6
		Apply to Toner Status and Easy setup of Samsung Cloud Print
V4.00.01.36 (21-Jul, 2016)	Fix Defect	Implement the latest flow of Printer ON.
		PC print job can be paused/cancelled using STOP hard key on printer.
		Improve slow USB PDF Printing
		Coverage Classification for page count is provided in Supplies Information Report. Same has to be displayed in SWS under Information > Supplies
		Improve an image registration problem by the ACR failure.
	Add Func.	Add calibration condition menu, calibration condition to cloning, Admin Password to cloning
		Add Best Buy additional cloning items.

※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
- If you are using USB connection, disconnect all other USB printers from the PC.
- The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.
  Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

How to update the firmware using a USB cable.

1. Make sure that the machine is connected to the PC with a USB cable.
2. Menu > Setup > Admin Setup > Firmware Upgrade > ON
3. Drag the firmware file(*.hd) and Drop down it on usblist2.exe.
   And then, firmware update will be started automatically.



4. The firmware update will start.
   Once the firmware update is complete, the machine will be rebooted automatically.

Updating from the Network

1. Go to the SyncThruWeb Service (SWS) main home page.
   Login as Admin in SyncThruWeb Service.
   NOTE: Login using the Administrator ID and Password established during initial machine setup.
2. Click [Maintenance] on the top menu.
   And then click [Firmware Upgrade] or Application Management > Application
3. Click Add button
4. Click [Browse]. Choose installation file by browsing file system. And click OK button
5. The uploading step will start. After this step, next step will be started automatically.
6. The firmware update will start.
7. Once the f/w update is complete, the machine power-off and power-on automatically.